



RESD1

ESD Air Discharge Voltage Meter



Description :

- Daily Check
- High Voltage Value
- Digital display
- Easy use and Safety operation

RESD1 is designed to measure the Voltage energy generated by ESD GUN air discharge mode. RESD1 is a handy monitoring device that you can use to confirm that your ESD GUN remains healthy before each ESD test.

Specifications :

Measurement range :

±0.00~19.99kV @ 20kV gear

±20.0~35.0kV @ 35kV gear

Display accuracy : ± 5%

Input resistance : 1000MΩ

Voltage division ratio : 1000:1

Dimension : 380×180×80 mm

Weight : < 1 kg

Power supply : 110/220Vac input / DC 5V,1A output.

Ground Clip lead : 1.6 meter.

Warranty : 1-year

利諾科技有限公司 Richtec Instruments Co., Ltd.

www.richtec.com.tw / Tel : +886-2-8912-1185 / sales@richtec.com.tw

23145 新北市新店區寶橋路235巷130號6樓之五

2023.05.26 V01